



# Power Inductor Design Guides

## How to utilize guides from the following list for DC-DC conversion circuits:

1. Determine current rating requirement (max current the inductor will see including ripple of typically 20%-40%).
2. Within Technical Data Column, locate guide(s) in which current rating requirement is within range.
3. Identify inductance utilizing preferred equation or the equations to the right.
4. Review description and optimize design to cost, efficiency or size.
5. If guide variety does not meet your needs, contact Abracon for specialized support.

$$L_{\text{BOOST}} > \frac{V_{\text{IN(MIN)}} \cdot (V_{\text{OUT}} - V_{\text{IN(MIN)}})}{f \cdot \Delta I_L \cdot V_{\text{OUT}}} H$$

$$L_{\text{BUCK}} > \frac{V_{\text{OUT}} \cdot (V_{\text{IN(MAX)}} - V_{\text{OUT}})}{f \cdot \Delta I_L \cdot V_{\text{IN(MAX)}}} H$$

## Design Guide Information

Guide Name	Inductance Range	Current Rating Range	DCR Range
<a href="#">ADG-PL-01</a>	0.100 µH - 10 µH	0.06 A - 0.7 A	100 mΩ - 5000 mΩ
<a href="#">ADG-PL-02</a>	12 µH - 68 µH	0.06 A - 0.7 A	110 mΩ - 3510 mΩ
<a href="#">ADG-PL-03</a>	100 µH - 680 µH	0.06 A - 0.7 A	480 mΩ - 15000 mΩ
<a href="#">ADG-PL-04</a>	0.100 µH - 10 µH	0.7 A - 1.6 A	40 mΩ - 570 mΩ
<a href="#">ADG-PL-05</a>	12 µH - 47 µH	0.7 A - 1.6 A	70 mΩ - 1050 mΩ
<a href="#">ADG-PL-06</a>	68 µH - 470 µH	0.7 A - 1.6 A	200 mΩ - 980 mΩ
<a href="#">ADG-PL-07</a>	0.240 µH - 4.7 µH	1.6 A - 5 A	15 mΩ - 180 mΩ
<a href="#">ADG-PL-08</a>	10 µH - 15 µH	1.6 A - 5 A	24 mΩ - 290 mΩ

Guide Name	Inductance Range	Current Rating Range	DCR Range
<a href="#">ADG-PL-09</a>	22 $\mu$ H - 100 $\mu$ H	1.6 A - 5 A	43 m $\Omega$ - 363 m $\Omega$
<a href="#">ADG-PL-10</a>	0.110 $\mu$ H - 1.0 $\mu$ H	5 A - 10 A	7.6 m $\Omega$ - 43 m $\Omega$
<a href="#">ADG-PL-11</a>	1.5 $\mu$ H - 4.7 $\mu$ H	5 A - 10 A	12 m $\Omega$ - 41 m $\Omega$
<a href="#">ADG-PL-12</a>	6.8 $\mu$ H - 100 $\mu$ H	5 A - 10 A	16.5 m $\Omega$ - 90 m $\Omega$
<a href="#">ADG-PL-13</a>	0.100 $\mu$ H - 1.0 $\mu$ H	10 A - 15 A	2.3 m $\Omega$ - 14.5 m $\Omega$
<a href="#">ADG-PL-14</a>	1.5 $\mu$ H - 4.7 $\mu$ H	10 A - 15 A	6.3 m $\Omega$ - 18 m $\Omega$
<a href="#">ADG-PL-15</a>	5.6 $\mu$ H - 47 $\mu$ H	10 A - 15 A	10 m $\Omega$ - 15 m $\Omega$
<a href="#">ADG-PL-16</a>	0.100 $\mu$ H - 1.0 $\mu$ H	15 A - 25 A	1.35 m $\Omega$ - 6.5 m $\Omega$
<a href="#">ADG-PL-17</a>	1.2 $\mu$ H - 4.7 $\mu$ H	15 A - 25 A	2.53 m $\Omega$ - 9.13 m $\Omega$
<a href="#">ADG-PL-18</a>	5.6 $\mu$ H - 22 $\mu$ H	15 A - 25 A	4.1 m $\Omega$ - 15.8 m $\Omega$
<a href="#">ADG-PL-19</a>	0.100 $\mu$ H - 1.0 $\mu$ H	25 A - 45 A	0.29 m $\Omega$ - 2.75 m $\Omega$
<a href="#">ADG-PL-20</a>	1.5 $\mu$ H - 8.2 $\mu$ H	70 A - 77 A	1.25 m $\Omega$ - 5.7 m $\Omega$
<a href="#">ADG-PL-21</a>	0.070 $\mu$ H - 1.5 $\mu$ H	45 A - 80 A	0.125 m $\Omega$ - 2.5 m $\Omega$